Einstellwerte für gedrehte Kontakte

Settings for closed turned contacts

Werkzeuge / Tools

97 52 63 A / 97 52 63 DG A

Hinweis: Das Einstellmaß und die Locator-Position der Crimpzange sind entsprechend dem Leiterquerschnitt anzupassen.
Zur Ermittlung der hier aufgeführten Crimpeinstellungen wurde ein handelsübliches, feindrähtiges Litzenkabel verwendet. Die ermittelten Werte sind lediglich Richtgrößen und ohne Gewähr. Die Crimpeinstellungen sind vom Anwender mit der jeweils eingesetzten Litze konkret zu prüfen.

Note: The crimping depth and the locator position on the crimping tool must be adjusted to match the conductor cross-section.
A standard, fine-stranded cable was used to determine the crimping settings listed here. The values given are for guidance only and are provided without warranty.
The user must verify the crimping settings specifically for the stranded cable being used.

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator-position
Harting	97 59 63 HU1	09 15 100 6101		M23	Signalstecker	0,72	0,08	1
Harting	97 59 63 HU1	09 15 100 6101		M23	Signalstecker	0,78	0,14	1
Harting	97 59 63 HU1	09 15 100 6101		M23	Signalstecker	0,82	0,25	1
Harting	97 59 63 HU1	09 15 100 6101		M23	Signalstecker	0,82	0,34	1
Harting	97 59 63 HU1	09 15 100 6101		M23	Signalstecker	0,90	0,56	1
Harting	97 59 63 HU1	09 15 100 6102		M23	Signalstecker	0,70	0,14	1
Harting	97 59 63 HU1	09 15 100 6102		M23	Signalstecker	0,76	0,25	1
Harting	97 59 63 HU1	09 15 100 6102		M23	Signalstecker	0,82	0,34	1
Harting	97 59 63 HU1	09 15 100 6102		M23	Signalstecker	0,90	0,50	1
Harting	97 59 63 HU1	09 15 100 6102		M23	Signalstecker	1,00	0,75	1
Harting	97 59 63 HU1	09 15 100 6102		M23	Signalstecker	1,10	1,00	1
Harting	97 59 63 HU1	09 15 100 6103		M23	Signalstecker	0,80	0,75	1
Harting	97 59 63 HU1	09 15 100 6103		M23	Signalstecker	0,86	1,00	1
Harting	97 59 63 HU1	09 15 100 6103		M23	Signalstecker	0,95	1,50	1
Harting	97 59 63 HU1	09 15 100 6111		M23	Signalstecker	0,65	0,14	3
Harting	97 59 63 HU1	09 15 100 6111		M23	Signalstecker	0,68	0,25	3
Harting	97 59 63 HU1	09 15 100 6111		M23	Signalstecker	0,72	0,34	3
Harting	97 59 63 HU1	09 15 100 6111		M23	Signalstecker	0,81	0,56	3
Harting	97 59 63 HU1	09 15 100 6111		M23	Signalstecker	0,95	0,75	3
Harting	97 59 63 HU1	09 15 100 6111		M23	Signalstecker	1,07	1,00	3
Harting	97 59 63 HU1	09 15 100 6121		M23	Signalstecker	0,88	0,75	4
Harting	97 59 63 HU1	09 15 100 6121		M23	Signalstecker	0,95	1,00	4
Harting	97 59 63 HU1	09 15 100 6121		M23	Signalstecker	1,05	1,50	4
Harting	97 59 63 HU1	09 15 100 6121		M23	Signalstecker	1,13	2,50	4
Harting	97 59 63 HU1	09 15 100 6201		M23	Signalstecker	0,75	0,08	2
Harting	97 59 63 HU1	09 15 100 6201		M23	Signalstecker	0,78	0,14	2
Harting	97 59 63 HU1	09 15 100 6201		M23	Signalstecker	0,82	0,25	2
Harting	97 59 63 HU1	09 15 100 6201		M23	Signalstecker	0,86	0,34	2
Harting	97 59 63 HU1	09 15 100 6201		M23	Signalstecker	0,90	0,56	2
Harting	97 59 63 HU1	09 15 100 6202		M23	Signalstecker	0,77	0,34	2
Harting	97 59 63 HU1	09 15 100 6202		M23	Signalstecker	0,82	0,56	2
Harting	97 59 63 HU1	09 15 100 6202		M23	Signalstecker	0,88	0,75	2
Harting	97 59 63 HU1	09 15 100 6202		M23	Signalstecker	0,95	1,00	2
Harting	97 59 63 HU1	09 15 100 6203		M23	Signalstecker	0,80	0,75	2
Harting	97 59 63 HU1	09 15 100 6203		M23	Signalstecker	0,86	1,00	2
Harting	97 59 63 HU1	09 15 100 6203		M23	Signalstecker	0,95	1,50	2
Harting	97 59 63 HU1	09 15 100 6211		M23	Signalstecker	0,70	0,14	2
Harting	97 59 63 HU1	09 15 100 6211		M23	Signalstecker	0,73	0,25	2
Harting	97 59 63 HU1	09 15 100 6211		M23	Signalstecker	0,77	0,34	2
Harting	97 59 63 HU1	09 15 100 6211		M23	Signalstecker	0,85	0,56	2
Harting	97 59 63 HU1	09 15 100 6212		M23	Signalstecker	0,70	0,34	2
Harting	97 59 63 HU1	09 15 100 6212		M23	Signalstecker	0,73	0,56	2
Harting	97 59 63 HU1	09 15 100 6212		M23	Signalstecker	0,77	0,75	2
Harting	97 59 63 HU1	09 15 100 6212		M23	Signalstecker	0,85	1,00	2
Harting	97 59 63 HU1	09 15 100 6221		M23	Signalstecker	1,25	0,75	5
Harting	97 59 63 HU1	09 15 100 6221		M23	Signalstecker	1,35	1,00	5
Harting	97 59 63 HU1	09 15 100 6221		M23	Signalstecker	1,45	1,50	5
Harting	97 59 63 HU1	09 15 100 6221		M23	Signalstecker	1,60	2,50	5
Hummel	97 59 63 HU1	7010901001		M16 / M23	Signalstecker	0,70	0,14	1
Hummel	97 59 63 HU1	7010901001		M16 / M23	Signalstecker	0,76	0,25	1
Hummel	97 59 63 HU1	7010901001		M16 / M23	Signalstecker	0,82	0,34	1
Hummel	97 59 63 HU1	7010901001		M16 / M23	Signalstecker	0,90	0,56	1
Hummel	97 59 63 HU1	7010901001		M16 / M23	Signalstecker	1,00	0,75	1
Hummel	97 59 63 HU1	7010901001		M16 / M23	Signalstecker	1,10	1,00	1
Hummel	97 59 63 HU1	7010901002		M16 / M23	Signalstecker	0,77	0,34	2
Hummel	97 59 63 HU1	7010901002		M16 / M23	Signalstecker	0,82	0,56	2

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator- position
Hummel	97 59 63 HU1	7010901002		M16 / M23	Signalstecker	0,88	0,75	2
Hummel	97 59 63 HU1	7010901002		M16 / M23	Signalstecker	0,95	1,00	2
Hummel	97 59 63 HU1	7010901012		M16 / M23	Signalstecker	0,75	0,08	2
Hummel	97 59 63 HU1	7010901012		M16 / M23	Signalstecker	0,78	0,14	2
Hummel	97 59 63 HU1	7010901012		M16 / M23	Signalstecker	0,82	0,25	2
Hummel	97 59 63 HU1	7010901012		M16 / M23	Signalstecker	0,86	0,34	2
Hummel	97 59 63 HU1	7010901012		M16 / M23	Signalstecker	0,90	0,56	2
Hummel	97 59 63 HU1	7010901021		M16 / M23	Signalstecker	0,80	0,75	1
Hummel	97 59 63 HU1	7010901021		M16 / M23	Signalstecker	0,86	1,00	1
Hummel	97 59 63 HU1	7010901021		M16 / M23	Signalstecker	0,95	1,50	1
Hummel	97 59 63 HU1	7010901022		M16 / M23	Signalstecker	0,80	0,75	2
Hummel	97 59 63 HU1	7010901022		M16 / M23	Signalstecker	0,86	1,00	2
Hummel	97 59 63 HU1	7010901022		M16 / M23	Signalstecker	0,95	1,50	2
Hummel	97 59 63 HU1	7010901031		M16 / M23	Signalstecker	0,72	0,08	1
Hummel	97 59 63 HU1	7010901031		M16 / M23	Signalstecker	0,78	0,14	1
Hummel	97 59 63 HU1	7010901031		M16 / M23	Signalstecker	0,82	0,25	1
Hummel	97 59 63 HU1	7010901031		M16 / M23	Signalstecker	0,86	0,34	1
Hummel	97 59 63 HU1	7010901031		M16 / M23	Signalstecker	0,90	0,56	1
Hummel	97 59 63 HU1	7010901501		M16 / M23	Signalstecker	0,65	0,14	3
Hummel	97 59 63 HU1	7010901501		M16 / M23	Signalstecker	0,68	0,25	3
Hummel	97 59 63 HU1	7010901501		M16 / M23	Signalstecker	0,72	0,34	3
Hummel	97 59 63 HU1	7010901501		M16 / M23	Signalstecker	0,81	0,56	3
Hummel	97 59 63 HU1	7010901501		M16 / M23	Signalstecker	0,95	0,75	3
Hummel	97 59 63 HU1	7010901501		M16 / M23	Signalstecker	1,07	1,00	3
Hummel	97 59 63 HU1	7010901502		M16 / M23	Signalstecker	0,88	0,34	2
Hummel	97 59 63 HU1	7010901502		M16 / M23	Signalstecker	0,95	0,56	2
Hummel	97 59 63 HU1	7010901502		M16 / M23	Signalstecker	1,05	0,75	2
Hummel	97 59 63 HU1	7010901502		M16 / M23	Signalstecker	1,13	1,00	2
Hummel	97 59 63 HU1	7010901512		M16 / M23	Signalstecker	0,70	0,14	2
Hummel	97 59 63 HU1	7010901512		M16 / M23	Signalstecker	0,73	0,25	2
Hummel	97 59 63 HU1	7010901512		M16 / M23	Signalstecker	0,77	0,34	2
Hummel	97 59 63 HU1	7010901512		M16 / M23	Signalstecker	0,85	0,56	2
Hummel	97 59 63 HU1	7010902001		M16 / M23	Signalstecker	1,25	0,75	4
Hummel	97 59 63 HU1	7010902001		M16 / M23	Signalstecker	1,35	1,00	4
Hummel	97 59 63 HU1	7010902001		M16 / M23	Signalstecker	1,45	1,50	4
Hummel	97 59 63 HU1	7010902001		M16 / M23	Signalstecker	1,60	2,50	4
Hummel	97 59 63 HU1	7010902002		M16 / M23	Signalstecker	1,25	0,75	5
Hummel	97 59 63 HU1	7010902002		M16 / M23	Signalstecker	1,35	1,00	5
Hummel	97 59 63 HU1	7010902002		M16 / M23	Signalstecker	1,45	1,50	5
Hummel	97 59 63 HU1	7010902002		M16 / M23	Signalstecker	1,60	2,50	5
Hummel	97 59 63 HU1	7010980801		M16 / M23	Signalstecker	0,57	0,08	10
Hummel	97 59 63 HU1	7010980801		M16 / M23	Signalstecker	0,60	0,14	10
Hummel	97 59 63 HU1	7010980801		M16 / M23	Signalstecker	0,64	0,25	10
Hummel	97 59 63 HU1	7010980801		M16 / M23	Signalstecker	0,73	0,34	10
Hummel	97 59 63 HU1	7010980802		M16 / M23	Signalstecker	0,57	0,08	10
Hummel	97 59 63 HU1	7010980802		M16 / M23	Signalstecker	0,60	0,14	10
Hummel	97 59 63 HU1	7010980802		M16 / M23	Signalstecker	0,64	0,25	10
Hummel	97 59 63 HU1	7010980802		M16 / M23	Signalstecker	0,73	0,34	10
Hummel	97 59 63 HU1	7010981001		M16 / M23	Signalstecker	0,60	0,08	7
Hummel	97 59 63 HU1	7010981001		M16 / M23	Signalstecker	0,63	0,14	7
Hummel	97 59 63 HU1	7010981001		M16 / M23	Signalstecker	0,66	0,25	7
Hummel	97 59 63 HU1	7010981001		M16 / M23	Signalstecker	0,69	0,35	7
Hummel	97 59 63 HU1	7010981001		M16 / M23	Signalstecker	0,75	0,50	7
Hummel	97 59 63 HU1	7010981001		M16 / M23	Signalstecker	0,83	0,75	7
Hummel	97 59 63 HU1	7010981002		M16 / M23	Signalstecker	0,60	0,08	8
Hummel	97 59 63 HU1	7010981002		M16 / M23	Signalstecker	0,63	0,14	8
Hummel	97 59 63 HU1	7010981002		M16 / M23	Signalstecker	0,66	0,25	8
Hummel	97 59 63 HU1	7010981002		M16 / M23	Signalstecker	0,69	0,34	8
Hummel	97 59 63 HU1	7010981002		M16 / M23	Signalstecker	0,75	0,56	8
Hummel	97 59 63 HU1	7010981002		M16 / M23	Signalstecker	0,83	0,75	8
Hummel	97 59 63 HU1	7010981201		M16 / M23	Signalstecker	0,70	0,50	2
Hummel	97 59 63 HU1	7010981201		M16 / M23	Signalstecker	0,73	0,75	2
Hummel	97 59 63 HU1	7010981201		M16 / M23	Signalstecker	0,79	1,00	2
Hummel	97 59 63 HU1	7010981201		M16 / M23	Signalstecker	0,88	1,50	2
Hummel	97 59 63 HU1	7010981202		M16 / M23	Signalstecker	0,70	0,50	2
Hummel	97 59 63 HU1	7010981202		M16 / M23	Signalstecker	0,73	0,75	2
Hummel	97 59 63 HU1	7010981202		M16 / M23	Signalstecker	0,79	1,00	2
Hummel	97 59 63 HU1	7010981202		M16 / M23	Signalstecker	0,88	1,50	2

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator- position
Hummel	97 59 63 HU1	7010981601		M16 / M23	Signalstecker	0,80	0,34	6
Hummel	97 59 63 HU1	7010981601		M16 / M23	Signalstecker	0,84	0,56	6
Hummel	97 59 63 HU1	7010981601		M16 / M23	Signalstecker	0,90	0,75	6
Hummel	97 59 63 HU1	7010981601		M16 / M23	Signalstecker	1,00	1,00	6
Hummel	97 59 63 HU1	7010981601		M16 / M23	Signalstecker	1,10	1,50	6
Hummel	97 59 63 HU1	7010981602		M16 / M23	Signalstecker	0,83	0,34	9
Hummel	97 59 63 HU1	7010981602		M16 / M23	Signalstecker	0,90	0,56	9
Hummel	97 59 63 HU1	7010981602		M16 / M23	Signalstecker	0,97	0,75	9
Hummel	97 59 63 HU1	7010981602		M16 / M23	Signalstecker	1,02	1,00	9
Hummel	97 59 63 HU1	7010981602		M16 / M23	Signalstecker	1,10	1,50	9
Hummel	97 59 63 HU1	7010982001		M16 / M23	Signalstecker	1,35	1,00	4
Hummel	97 59 63 HU1	7010982001		M16 / M23	Signalstecker	1,45	1,50	4
Hummel	97 59 63 HU1	7010982001		M16 / M23	Signalstecker	1,60	2,50	4
Hummel	97 59 63 HU1	7010982002		M16 / M23	Signalstecker	1,35	1,00	5
Hummel	97 59 63 HU1	7010982002		M16 / M23	Signalstecker	1,45	1,50	5
Hummel	97 59 63 HU1	7010982002		M16 / M23	Signalstecker	1,60	2,50	5
Hummel	97 59 63 HU1	70109D10D2		-	-	0,96	0,75	11
Hummel	97 59 63 HU1	70109D10D2		-	-	1,00	1,00	11