Einstellwerte für gedrehte Kontakte
Settings for closed turned contacts

Werkzeuge / Tools
97 52 63 A / 97 52 63 DG A

Hinweis: Das Einstellmaß und die Locator-Position der Crimpzange sind entsprechend dem Leiterquerschnitt anzupassen.
Zur Ermittlung der hier aufgeführten Crimpeinstellungen wurde ein handelsübliches, feindrähtiges Litzenkabel verwendet. Die ermittelten Werte sind lediglich Richtgrößen und ohne Gewähr. Die Crimpeinstellungen sind vom Anwender mit der jeweils eingesetzten Litze konkret zu prüfen.

Note: The crimping depth and the locator position on the crimping tool must be adjusted to match the conductor cross-section.
A standard, fine-stranded cable was used to determine the crimping settings listed here. The values given are for guidance only and are provided without warranty.
The user must verify the crimping settings specifically for the stranded cable being used.

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator-position
Phoenix Contact	97 59 63 PC4	CC-0,8-ST-0,34-MS AU	1452372	-	-	0,40	0,08	1
Phoenix Contact	97 59 63 PC4	CC-0,8-ST-0,34-MS AU	1452372	-	-	0,45	0,14	1
Phoenix Contact	97 59 63 PC4	CC-0,8-ST-0,34-MS AU	1452372	-	-	0,50	0,25	1
Phoenix Contact	97 59 63 PC4	CC-0,8-ST-0,34-MS AU	1452372	-	-	0,60	0,34	1
Phoenix Contact	97 59 63 PC4	CC-1,0-ST-0,34-MS AU	1452356	-	-	0,40	0,08	1
Phoenix Contact	97 59 63 PC4	CC-1,0-ST-0,34-MS AU	1452356	-	-	0,45	0,14	1
Phoenix Contact	97 59 63 PC4	CC-1,0-ST-0,34-MS AU	1452356	-	-	0,50	0,25	1
Phoenix Contact	97 59 63 PC4	CC-1,0-ST-0,34-MS AU	1452356	-	-	0,60	0,34	1
Phoenix Contact	97 59 63 PC4	CC-1,0-ST-0,34-MS AU	1452356	-	-	0,70	AWG 22	1
Phoenix Contact	97 59 63 PC4	CC-1,0-T-1,0-M AU PU100	1452356	-	-	0,40	0,08	1
Phoenix Contact	97 59 63 PC4	CC-1,0-T-1,0-M AU PU100	1452356	-	-	0,45	0,14	1
Phoenix Contact	97 59 63 PC4	CC0,6-RS-0,34M AU PU100	1423643	-	-	0,68	0,35	5
Phoenix Contact	97 59 63 PC4	CC0,6-RS-0,34M AU PU100	1418784	-	-	0,75	AWG 24	8
Phoenix Contact	97 59 63 PC4	CC0,6-RS-0,34M AU PU100	1418784	-	-	0,70	AWG 26	8
Phoenix Contact	97 59 63 PC4	CC0,6-RS-0,34M AU PU100	1418784	-	-	0,65	AWG 28	8
Phoenix Contact	97 59 63 PC4	CC0,6-TS-0,34M AU	1423643	-	-	0,50	0,14	5
Phoenix Contact	97 59 63 PC4	CC0,6-TS-0,34M AU	1423643	-	-	0,55	0,25	5
Phoenix Contact	97 59 63 PC4	CC0,6-TS-0,34M AU	1423643	-	-	0,60	0,34	5
Phoenix Contact	97 59 63 PC4	CC0,6-TS-0,34M AU	1423643	-	-	0,60	AWG 22	5
Phoenix Contact	97 59 63 PC4	CC0,6-TS-0,34M AU	1423643	-	-	0,55	AWG 24	5
Phoenix Contact	97 59 63 PC4	CC0,6-TS-0,34M AU	1423643	-	-	0,50	AWG 26	5
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34F AU	1319950	-	-	0,50	0,14	7
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34F AU	1319950	-	-	0,55	0,25	7
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34F AU	1319950	-	-	0,60	0,34	7
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34F AU	1319950	-	-	0,60	AWG 22	7
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34F AU	1319950	-	-	0,55	AWG 24	7
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34F AU	1319950	-	-	0,50	AWG 26	7
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34M AU	1319949	-	-	0,50	0,14	11
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34M AU	1319949	-	-	0,55	0,25	11
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34M AU	1319949	-	-	0,60	0,34	11
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34M AU	1319949	-	-	0,60	AWG 22	11
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34M AU	1319949	-	-	0,55	AWG 24	11
Phoenix Contact	97 59 63 PC4	CC0,8-TS-0,34M AU	1319949	-	-	0,50	AWG 26	11
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423643	-	-	0,59	0,14	5
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423643	-	-	0,61	0,25	5
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423646	-	-	0,61	0,34	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423646	-	-	0,74	0,50	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423646	-	-	0,78	0,75	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423646	-	-	0,85	1,00	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423646	-	-	0,78	AWG 18	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1418788	-	-	0,80	AWG 20	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423646	-	-	0,74	AWG 20	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1418788	-	-	0,75	AWG 22	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1418789	-	-	0,60	AWG 22	5
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1418790	-	-	0,60	AWG 22	5
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50F AU PU100	1423646	-	-	0,61	AWG 22	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1423645	-	-	0,61	0,34	11
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1423645	-	-	0,74	0,50	11
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1423645	-	-	0,78	0,75	11
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1423645	-	-	0,85	1,00	11
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1423645	-	-	0,78	AWG 18	11
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1418786	-	-	0,80	AWG 20	8
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1423645	-	-	0,74	AWG 20	11
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1418786	-	-	0,75	AWG 22	8
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1423645	-	-	0,61	AWG 22	11
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1418787	-	-	0,75	AWG 24	7

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator- position
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1418786	-	-	0,70	AWG 24	8
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1418788	-	-	0,70	AWG 24	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1418787	-	-	0,70	AWG 26	7
Phoenix Contact	97 59 63 PC4	CC1,0-RS-0,50M AU PU100	1418787	-	-	0,65	AWG 28	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34F AU	1064041	-	-	0,50	0,14	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34F AU	1064041	-	-	0,55	0,25	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34F AU	1064041	-	-	0,60	0,34	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34F AU	1064041	-	-	0,60	AWG 22	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34F AU	1064041	-	-	0,55	AWG 24	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34F AU	1064041	-	-	0,50	AWG 26	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34M AU	1064040	-	-	0,50	0,14	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34M AU	1064040	-	-	0,55	0,25	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34M AU	1064040	-	-	0,60	0,34	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34M AU	1064040	-	-	0,60	AWG 22	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34M AU	1064040	-	-	0,55	AWG 24	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-0,34M AU	1064040	-	-	0,50	AWG 26	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00F AU PU100	1423646	-	-	0,53	0,34	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00F AU PU100	1423646	-	-	0,60	0,50	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00F AU PU100	1423646	-	-	0,70	0,75	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00F AU PU100	1423646	-	-	0,83	1,00	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00F AU PU100	1423646	-	-	0,70	AWG 18	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00F AU PU100	1423646	-	-	0,60	AWG 20	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00F AU PU100	1423646	-	-	0,53	AWG 22	7
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00M AU PU100	1423645	-	-	0,53	0,34	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00M AU PU100	1423645	-	-	0,60	0,50	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00M AU PU100	1423645	-	-	0,70	0,75	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00M AU PU100	1423645	-	-	0,83	1,00	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00M AU PU100	1423645	-	-	0,70	AWG 18	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00M AU PU100	1423645	-	-	0,60	AWG 20	11
Phoenix Contact	97 59 63 PC4	CC1,0-TS-1,00M AU PU100	1423645	-	-	0,53	AWG 22	11
Phoenix Contact	97 59 63 PC4	CUC-DSC-C1BAU-S/DSC22	1418789	HC-M-DSUB-C	D - SUB	0,60	AWG 22	5
Phoenix Contact	97 59 63 PC4	CUC-DSC-C1BAU-S/DSC24	1418786	HC-M-DSUB-C	D - SUB	0,80	AWG 20	8
Phoenix Contact	97 59 63 PC4	CUC-DSC-C1BAU-S/DSC24	1418786	HC-M-DSUB-C	D - SUB	0,75	AWG 22	8
Phoenix Contact	97 59 63 PC4	CUC-DSC-C1BAU-S/DSC24	1418786	HC-M-DSUB-C	D - SUB	0,70	AWG 24	8
Phoenix Contact	97 59 63 PC4	CUC-DSC-C1BAU-S/DSC28	1418784	HC-M-DSUB-C	D - SUB	0,75	AWG 24	8
Phoenix Contact	97 59 63 PC4	CUC-DSC-C1BAU-S/DSC28	1418784	HC-M-DSUB-C	D - SUB	0,70	AWG 26	8
Phoenix Contact	97 59 63 PC4	CUC-DSC-C1BAU-S/DSC28	1418784	HC-M-DSUB-C	D - SUB	0,65	AWG 28	8
Phoenix Contact	97 59 63 PC4	CUC-DSC-J1BAU-S/DSC22	1418790	HC-M-DSUB-C	D - SUB	0,60	AWG 22	9
Phoenix Contact	97 59 63 PC4	CUC-DSC-J1BAU-S/DSC24	1418788	HC-M-DSUB-C	D - SUB	0,80	AWG 20	7
Phoenix Contact	97 59 63 PC4	CUC-DSC-J1BAU-S/DSC24	1418788	HC-M-DSUB-C	D - SUB	0,75	AWG 22	7
Phoenix Contact	97 59 63 PC4	CUC-DSC-J1BAU-S/DSC24	1418788	HC-M-DSUB-C	D - SUB	0,70	AWG 24	7
Phoenix Contact	97 59 63 PC4	CUC-DSC-J1BAU-S/DSC28	1418787	HC-M-DSUB-C	D - SUB	0,75	AWG 24	7
Phoenix Contact	97 59 63 PC4	CUC-DSC-J1BAU-S/DSC28	1418787	HC-M-DSUB-C	D - SUB	0,70	AWG 26	7
Phoenix Contact	97 59 63 PC4	CUC-DSC-J1BAU-S/DSC28	1418787	HC-M-DSUB-C	D - SUB	0,65	AWG 28	7
Phoenix Contact	97 59 63 PC4	VS-BU-CD-HD-1,0/13,5/0,37	1655263	-	-	0,65	0,34	9
Phoenix Contact	97 59 63 PC4	VS-BU-CD-HD-1,0/13,5/0,37	1655276	-	-	0,65	0,34	5
Phoenix Contact	97 59 63 PC4	VS-ST-CD-1,0/14,8/0,2	1688971	-	-	0,75	AWG 24	3
Phoenix Contact	97 59 63 PC4	VS-ST-CD-1,0/14,8/0,2	1688971	-	-	0,70	AWG 26	3
Phoenix Contact	97 59 63 PC4	VS-ST-CD-1,0/14,8/0,2	1688971	-	-	0,65	AWG 28	3