Einstellwerte für gedrehte Kontakte
Settings for closed turned contacts

Werkzeuge / Tools
97 52 63 A / 97 52 63 DG A

Hinweis: Das Einstellmaß und die Locator-Position der Crimpzange sind entsprechend dem Leiterquerschnitt anzupassen.
Zur Ermittlung der hier aufgeführten Crimpeinstellungen wurde ein handelsübliches, feindrähtiges Litzenkabel verwendet. Die ermittelten Werte sind lediglich Richtgrößen und ohne Gewähr. Die Crimpeinstellungen sind vom Anwender mit der jeweils eingesetzten Litze konkret zu prüfen.

Note: The crimping depth and the locator position on the crimping tool must be adjusted to match the conductor cross-section.
A standard, fine-stranded cable was used to determine the crimping settings listed here. The values given are for guidance only and are provided without warranty.
The user must verify the crimping settings specifically for the stranded cable being used.

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator-position
Phoenix Contact	97 59 63 PC1	CR-06TP0,34-0,50/HYB	1680551	-	-	0,63	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	CR-06TP0,34-0,50/HYB	1680551	-	-	0,66	0,50	Stift 02
Phoenix Contact	97 59 63 PC1	CR-06TS0,08-0,34/HYB	1680547	-	-	0,52	0,08	Stift 02
Phoenix Contact	97 59 63 PC1	CR-06TS0,08-0,34/HYB	1680547	-	-	0,51	0,14	Stift 02
Phoenix Contact	97 59 63 PC1	CR-06TS0,08-0,34/HYB	1680547	-	-	0,55	0,25	Stift 02
Phoenix Contact	97 59 63 PC1	CR-06TS0,08-0,34/HYB	1680547	-	-	0,61	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	CR-06TS0,34-0,50/HYB	1680551	-	-	0,63	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	CR-06TS0,34-0,50/HYB	1680551	-	-	0,66	0,50	Stift 02
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,46	0,06	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,50	0,08	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,53	0,14	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,65	0,25	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,69	0,34	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,80	0,50	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,85	0,75	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,90	1,00	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,06-1,00/HYB/SIG	1680546	-	-	0,84	AWG 18	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,50-1,50/HYB/PW	1680540	-	-	0,75	0,50	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,50-1,50/HYB/PW	1680540	-	-	0,90	0,75	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,50-1,50/HYB/PW	1680540	-	-	0,95	1,00	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,50-1,50/HYB/PW	1680540	-	-	1,00	1,50	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,50-1,50/HYB/PW	1680540	-	-	0,99	AWG 16	1
Phoenix Contact	97 59 63 PC1	CR-10TP0,50-1,50/HYB/PW	1680540	-	-	0,80	AWG 19	1
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,46	0,06	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,50	0,08	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,53	0,14	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,65	0,25	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,69	0,34	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,80	0,50	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,85	0,75	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,90	1,00	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,06-1,00/HYB/SIG	1680541	-	-	0,84	AWG 18	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,50-1,50/HYB/PW	1680535	-	-	0,89	0,50	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,50-1,50/HYB/PW	1680535	-	-	0,93	0,75	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,50-1,50/HYB/PW	1680535	-	-	0,89	1,00	3
Phoenix Contact	97 59 63 PC1	CR-10TS0,50-1,50/HYB/PW	1680535	-	-	0,92	1,50	3
Phoenix Contact	97 59 63 PC1	SB-10KP0,06-1,00	1244924	-	-	0,44	0,06	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,06-1,00	1244924	-	-	0,51	0,08	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,06-1,00	1244924	-	-	0,53	0,14	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,06-1,00	1244924	-	-	0,69	0,25	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,06-1,00	1244924	-	-	0,72	0,34	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,06-1,00	1244924	-	-	0,78	0,50	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,06-1,00	1244924	-	-	0,77	0,75	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,06-1,00	1244924	-	-	0,83	1,00	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,75	0,50	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,75	0,50	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,90	0,75	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,90	0,75	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,95	1,00	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,95	1,00	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	1,00	1,50	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	1,00	1,50	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,99	AWG 16	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,99	AWG 16	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,80	AWG 19	11
Phoenix Contact	97 59 63 PC1	SB-10KP0,50-1,50	1244925	-	-	0,80	AWG 19	11

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator-position
Phoenix Contact	97 59 63 PC1	SB-10KP001	1623607	-	-	0,53	0,06	11
Phoenix Contact	97 59 63 PC1	SB-10KP001	1623607	-	-	0,55	0,08	11
Phoenix Contact	97 59 63 PC1	SB-10KP001	1623607	-	-	0,60	0,14	11
Phoenix Contact	97 59 63 PC1	SB-10KP001	1623607	-	-	0,65	0,25	11
Phoenix Contact	97 59 63 PC1	SB-10KP002	1623611	-	-	1,00	0,35	11
Phoenix Contact	97 59 63 PC1	SB-10KP002	1623611	-	-	1,05	0,50	11
Phoenix Contact	97 59 63 PC1	SB-10KP003	1623612	-	-	1,00	0,50	11
Phoenix Contact	97 59 63 PC1	SB-10KP003	1623612	-	-	1,10	0,75	11
Phoenix Contact	97 59 63 PC1	SB-10KP003	1623612	-	-	1,20	1,00	11
Phoenix Contact	97 59 63 PC1	SB-10KP004	1623613	-	-	1,00	1,00	11
Phoenix Contact	97 59 63 PC1	SB-10KP004	1623613	-	-	1,15	1,50	11
Phoenix Contact	97 59 63 PC1	SB-10KS0,06-1,00	1244919	-	-	0,44	0,06	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,06-1,00	1244919	-	-	0,51	0,08	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,06-1,00	1244919	-	-	0,53	0,14	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,06-1,00	1244919	-	-	0,69	0,25	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,06-1,00	1244919	-	-	0,72	0,34	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,06-1,00	1244919	-	-	0,78	0,50	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,06-1,00	1244919	-	-	0,77	0,75	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,06-1,00	1244919	-	-	0,83	1,00	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,50-1,50	1244920	-	-	0,75	0,50	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,50-1,50	1244920	-	-	0,90	0,75	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,50-1,50	1244920	-	-	0,95	1,00	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,50-1,50	1244920	-	-	1,00	1,50	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,50-1,50	1244920	-	-	0,99	AWG 16	3
Phoenix Contact	97 59 63 PC1	SB-10KS0,50-1,50	1244920	-	-	0,80	AWG 19	3
Phoenix Contact	97 59 63 PC1	SB-10KS001	1623603	-	-	0,53	0,06	3
Phoenix Contact	97 59 63 PC1	SB-10KS001	1623603	-	-	0,55	0,08	3
Phoenix Contact	97 59 63 PC1	SB-10KS001	1623603	-	-	0,60	0,14	3
Phoenix Contact	97 59 63 PC1	SB-10KS001	1623603	-	-	0,65	0,25	3
Phoenix Contact	97 59 63 PC1	SB-10KS002	1623604	-	-	1,00	0,35	3
Phoenix Contact	97 59 63 PC1	SB-10KS002	1623604	-	-	1,05	0,50	3
Phoenix Contact	97 59 63 PC1	SB-10KS003	1623605	-	-	1,00	0,50	3
Phoenix Contact	97 59 63 PC1	SB-10KS003	1623605	-	-	1,10	0,75	3
Phoenix Contact	97 59 63 PC1	SB-10KS003	1623605	-	-	1,20	1,00	3
Phoenix Contact	97 59 63 PC1	SB-10KS004	1623606	-	-	1,00	1,00	3
Phoenix Contact	97 59 63 PC1	SB-10KS004	1623606	-	-	1,15	1,50	3
Phoenix Contact	97 59 63 PC1	SF-06KP0,06-0,25	1237992	-	-	0,43	0,06	Stift 05
Phoenix Contact	97 59 63 PC1	SF-06KP0,06-0,25	1237992	-	-	0,51	0,08	Stift 05
Phoenix Contact	97 59 63 PC1	SF-06KP0,06-0,25	1237992	-	-	0,52	0,14	Stift 05
Phoenix Contact	97 59 63 PC1	SF-06KP0,06-0,25	1237992	-	-	0,61	0,25	Stift 05
Phoenix Contact	97 59 63 PC1	SF-06KS0,06-0,25	1237993	-	-	0,43	0,06	Stift 06
Phoenix Contact	97 59 63 PC1	SF-06KS0,06-0,25	1237993	-	-	0,51	0,08	Stift 06
Phoenix Contact	97 59 63 PC1	SF-06KS0,06-0,25	1237993	-	-	0,52	0,14	Stift 06
Phoenix Contact	97 59 63 PC1	SF-06KS0,06-0,25	1237993	-	-	0,61	0,25	Stift 06
Phoenix Contact	97 59 63 PC1	SF-08KP010	1621574	-	-	0,50	0,08	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KP010	1621574	-	-	0,55	0,14	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KP010	1621574	-	-	0,60	0,25	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KP020	1621575	-	-	0,67	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KP020	1621575	-	-	0,75	0,50	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KS010	1621571	-	-	0,50	0,08	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KS010	1621571	-	-	0,55	0,14	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KS010	1621571	-	-	0,60	0,25	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KS020	1621573	-	-	0,67	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	SF-08KS020	1621573	-	-	0,75	0,50	Stift 02
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,46	0,06	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,50	0,08	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,53	0,14	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,65	0,25	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,69	0,34	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,80	0,50	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,85	0,75	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,90	1,00	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,06-1,00	1241921	-	-	0,84	AWG 18	1
Phoenix Contact	97 59 63 PC1	SF-10KP0,50-1,50	1242293	-	-	0,75	0,50	8
Phoenix Contact	97 59 63 PC1	SF-10KP0,50-1,50	1242293	-	-	0,90	0,75	8
Phoenix Contact	97 59 63 PC1	SF-10KP0,50-1,50	1242293	-	-	0,95	1,00	8
Phoenix Contact	97 59 63 PC1	SF-10KP0,50-1,50	1242293	-	-	1,00	1,50	8
Phoenix Contact	97 59 63 PC1	SF-10KP0,50-1,50	1242293	-	-	0,92	AWG 16	8

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator- position
Phoenix Contact	97 59 63 PC1	SF-10KP004	1607355	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,70	0,14	1
Phoenix Contact	97 59 63 PC1	SF-10KP004	1607355	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,75	0,25	1
Phoenix Contact	97 59 63 PC1	SF-10KP004	1607355	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,80	0,35	1
Phoenix Contact	97 59 63 PC1	SF-10KP004	1607355	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,88	0,50	1
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,40	0,06	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,45	0,08	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,53	0,14	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,62	0,25	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,69	0,34	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,74	0,50	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,78	0,75	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,85	1,00	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,06-1,00	1241922	-	-	0,86	AWG 18	3
Phoenix Contact	97 59 63 PC1	SF-10KS0,50-1,50	1241923	-	-	0,89	0,50	8
Phoenix Contact	97 59 63 PC1	SF-10KS0,50-1,50	1241923	-	-	0,93	0,75	8
Phoenix Contact	97 59 63 PC1	SF-10KS0,50-1,50	1241923	-	-	0,89	1,00	8
Phoenix Contact	97 59 63 PC1	SF-10KS0,50-1,50	1241923	-	-	0,92	1,50	8
Phoenix Contact	97 59 63 PC1	SF-10KS0,50-1,50	1241923	-	-	0,92	AWG 16	8
Phoenix Contact	97 59 63 PC1	SF-10KS004	1607356	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,70	0,14	3
Phoenix Contact	97 59 63 PC1	SF-10KS004	1607356	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,75	0,25	3
Phoenix Contact	97 59 63 PC1	SF-10KS004	1607356	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,80	0,35	3
Phoenix Contact	97 59 63 PC1	SF-10KS004	1607356	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,88	0,50	3
Phoenix Contact	97 59 63 PC1	SF-10KS010	1605481	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,60	0,14	3
Phoenix Contact	97 59 63 PC1	SF-10KS010	1605481	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,65	0,25	3
Phoenix Contact	97 59 63 PC1	SF-10KS010	1605481	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,70	0,35	3
Phoenix Contact	97 59 63 PC1	SF-10KS010	1605481	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,78	0,50	3
Phoenix Contact	97 59 63 PC1	SF-10KS010	1605481	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,90	0,75	3
Phoenix Contact	97 59 63 PC1	SF-10KS010	1605481	ConPower P20, F30, P30 / M17, M23	SF- Serie	1,00	1,00	3
Phoenix Contact	97 59 63 PC1	SF-20KP004		ConPower P30, P70 / M23	SF - Serie	1,05	0,75	2
Phoenix Contact	97 59 63 PC1	SF-20KP004		ConPower P30, P70 / M23	SF - Serie	1,15	1,00	2
Phoenix Contact	97 59 63 PC1	SF-20KP004		ConPower P30, P70 / M23	SF - Serie	1,30	1,50	2
Phoenix Contact	97 59 63 PC1	SF-20KP021		-	-	0,65	0,25	10
Phoenix Contact	97 59 63 PC1	SF-20KP021		-	-	0,70	0,35	10
Phoenix Contact	97 59 63 PC1	SF-20KP021		-	-	0,78	0,50	10
Phoenix Contact	97 59 63 PC1	SF-20KP021		-	-	0,90	0,75	10
Phoenix Contact	97 59 63 PC1	SF-20KP021		-	-	1,00	1,00	10
Phoenix Contact	97 59 63 PC1	SF-20KP022		-	-	1,40	1,50	10
Phoenix Contact	97 59 63 PC1	SF-20KP022		-	-	1,55	2,50	10
Phoenix Contact	97 59 63 PC1	SF-20KS021		-	-	0,65	0,25	10
Phoenix Contact	97 59 63 PC1	SF-20KS021		-	-	0,70	0,35	10
Phoenix Contact	97 59 63 PC1	SF-20KS021		-	-	0,78	0,50	10
Phoenix Contact	97 59 63 PC1	SF-20KS021		-	-	0,90	0,75	10
Phoenix Contact	97 59 63 PC1	SF-20KS021		-	-	1,00	1,00	10
Phoenix Contact	97 59 63 PC1	SF-20KS022		-	-	1,40	1,50	10
Phoenix Contact	97 59 63 PC1	SF-20KS022		-	-	1,55	2,50	10
Phoenix Contact	97 59 63 PC1	SF-6AP2000	1605554	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,60	0,14	1
Phoenix Contact	97 59 63 PC1	SF-6AP2000	1605554	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,65	0,25	1
Phoenix Contact	97 59 63 PC1	SF-6AP2000	1605554	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,70	0,35	1
Phoenix Contact	97 59 63 PC1	SF-6AP2000	1605554	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,78	0,50	1
Phoenix Contact	97 59 63 PC1	SF-6AP2000	1605554	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,90	0,75	1
Phoenix Contact	97 59 63 PC1	SF-6AP2000	1605554	ConPower P20, F30, P30 / M17, M23	SF - Serie	1,00	1,00	1
Phoenix Contact	97 59 63 PC1	SF-6AS2000	1605557	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,65	0,25	3
Phoenix Contact	97 59 63 PC1	SF-6AS2000	1605557	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,70	0,35	3
Phoenix Contact	97 59 63 PC1	SF-6AS2000	1605557	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,78	0,50	3

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator-position
Phoenix Contact	97 59 63 PC1	SF-6AS2000	1605557	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,90	0,75	3
Phoenix Contact	97 59 63 PC1	SF-6AS2000	1605557	ConPower P20, F30, P30 / M17, M23	SF- Serie	1,00	1,00	3
Phoenix Contact	97 59 63 PC1	SF-6CP2000	1605559	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,52	0,06	1
Phoenix Contact	97 59 63 PC1	SF-6CP2000	1605559	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,55	0,08	1
Phoenix Contact	97 59 63 PC1	SF-6CP2000	1605559	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,60	0,14	1
Phoenix Contact	97 59 63 PC1	SF-6CP2000	1605559	ConPower P20, F30, P30 / M17, M23	SF - Serie	0,65	0,25	1
Phoenix Contact	97 59 63 PC1	SF-6CS2000	1605562	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,52	0,06	3
Phoenix Contact	97 59 63 PC1	SF-6CS2000	1605562	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,55	0,08	3
Phoenix Contact	97 59 63 PC1	SF-6CS2000	1605562	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,60	0,14	3
Phoenix Contact	97 59 63 PC1	SF-6CS2000	1605562	ConPower P20, F30, P30 / M17, M23	SF- Serie	0,65	0,25	3
Phoenix Contact	97 59 63 PC1	SF-6DP2000	1607406	ConPower F30, P30 / M23	SF- Serie	0,80	0,50	1
Phoenix Contact	97 59 63 PC1	SF-6DP2000	1607406	ConPower F30, P30 / M23	SF- Serie	0,88	0,75	1
Phoenix Contact	97 59 63 PC1	SF-6DP2000	1607406	ConPower F30, P30 / M23	SF- Serie	1,00	1,00	1
Phoenix Contact	97 59 63 PC1	SF-6DP2000	1607406	ConPower F30, P30 / M23	SF- Serie	1,20	1,50	2
Phoenix Contact	97 59 63 PC1	SF-6FS2000	1605566	ConPower F30, P30 / M23	SF- Serie	0,80	0,50	3
Phoenix Contact	97 59 63 PC1	SF-6FS2000	1605566	ConPower F30, P30 / M23	SF- Serie	0,88	0,75	3
Phoenix Contact	97 59 63 PC1	SF-6FS2000	1605566	ConPower F30, P30 / M23	SF- Serie	1,00	1,00	3
Phoenix Contact	97 59 63 PC1	SF-6FS2000	1605566	ConPower F30, P30 / M23	SF- Serie	1,20	1,50	8
Phoenix Contact	97 59 63 PC1	SF-7PP2000	1510547	ConPower P30, P70 / M23	SF - Serie	0,95	0,75	2
Phoenix Contact	97 59 63 PC1	SF-7PP2000	1510547	ConPower P30, P70 / M23	SF - Serie	1,05	1,00	2
Phoenix Contact	97 59 63 PC1	SF-7QP2000	1605639	ConPower P30, P70 / M23	SF - Serie	1,20	1,00	2
Phoenix Contact	97 59 63 PC1	SF-7QP2000	1605639	ConPower P30, P70 / M23	SF - Serie	1,35	1,50	2
Phoenix Contact	97 59 63 PC1	SF-7QP2000	1605639	ConPower P30, P70 / M23	SF - Serie	1,60	2,50	2
Phoenix Contact	97 59 63 PC1	SF-7RP2000	1510582	ConPower P30, P70 / M23	SF - Serie	0,70	0,14	2
Phoenix Contact	97 59 63 PC1	SF-7RP2000	1510582	ConPower P30, P70 / M23	SF - Serie	0,75	0,25	2
Phoenix Contact	97 59 63 PC1	SH-08KP0,06-0,34	1244458	-	-	0,38	0,06	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KP0,06-0,34	1244458	-	-	0,52	0,08	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KP0,06-0,34	1244458	-	-	0,51	0,14	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KP0,06-0,34	1244458	-	-	0,55	0,25	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KP0,06-0,34	1244458	-	-	0,61	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KP0,34-0,50	1244459	-	-	0,63	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KP0,34-0,50	1244459	-	-	0,66	0,50	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KS0,06-0,34	1244455	-	-	0,38	0,06	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KS0,06-0,34	1244455	-	-	0,52	0,08	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KS0,06-0,34	1244455	-	-	0,51	0,14	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KS0,06-0,34	1244455	-	-	0,55	0,25	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KS0,06-0,34	1244455	-	-	0,61	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KS0,34-0,50	1244457	-	-	0,63	0,34	Stift 02
Phoenix Contact	97 59 63 PC1	SH-08KS0,34-0,50	1244457	-	-	0,66	0,50	Stift 02
Phoenix Contact	97 59 63 PC1	ST-06KP0,06-0,34	1242311	-	-	0,38	0,06	6
Phoenix Contact	97 59 63 PC1	ST-06KP0,06-0,34	1242311	-	-	0,52	0,08	6
Phoenix Contact	97 59 63 PC1	ST-06KP0,06-0,34	1242311	-	-	0,51	0,14	6
Phoenix Contact	97 59 63 PC1	ST-06KP0,06-0,34	1242311	-	-	0,55	0,25	6
Phoenix Contact	97 59 63 PC1	ST-06KP0,06-0,34	1242311	-	-	0,61	0,34	6
Phoenix Contact	97 59 63 PC1	ST-06KP0,34-0,50	1242312	-	-	0,63	0,34	6
Phoenix Contact	97 59 63 PC1	ST-06KP0,34-0,50	1242312	-	-	0,66	0,50	6
Phoenix Contact	97 59 63 PC1	ST-06KP010	1607577	ConPower P20 / M17	ST- Serie	0,48	0,06	6
Phoenix Contact	97 59 63 PC1	ST-06KP010	1607577	ConPower P20 / M17	ST- Serie	0,50	0,08	6
Phoenix Contact	97 59 63 PC1	ST-06KP010	1607577	ConPower P20 / M17	ST- Serie	0,55	0,14	6
Phoenix Contact	97 59 63 PC1	ST-06KP010	1607577	ConPower P20 / M17	ST- Serie	0,60	0,25	6
Phoenix Contact	97 59 63 PC1	ST-06KP020	1607578	ConPower P20 / M17	ST- Serie	0,55	0,14	6
Phoenix Contact	97 59 63 PC1	ST-06KP020	1607578	ConPower P20 / M17	ST- Serie	0,60	0,25	6
Phoenix Contact	97 59 63 PC1	ST-06KP020	1607578	ConPower P20 / M17	ST- Serie	0,65	0,35	6
Phoenix Contact	97 59 63 PC1	ST-06KP030	1607579	ConPower P20 / M17	ST- Serie	0,65	0,35	6
Phoenix Contact	97 59 63 PC1	ST-06KP030	1607579	ConPower P20 / M17	ST- Serie	0,73	0,50	6
Phoenix Contact	97 59 63 PC1	ST-06KS0,06-0,34	1242314	-	-	0,38	0,06	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS0,06-0,34	1242314	-	-	0,52	0,08	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS0,06-0,34	1242314	-	-	0,51	0,14	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS0,06-0,34	1242314	-	-	0,55	0,25	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS0,06-0,34	1242314	-	-	0,61	0,34	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS0,34-0,50	1242315	-	-	0,63	0,34	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS0,34-0,50	1242315	-	-	0,66	0,50	Stift 01

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator- position
Phoenix Contact	97 59 63 PC1	ST-06KS010	1607580	ConPower P20 / M17	ST- Serie	0,48	0,06	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS010	1607580	ConPower P20 / M17	ST- Serie	0,50	0,08	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS010	1607580	ConPower P20 / M17	ST- Serie	0,55	0,14	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS010	1607580	ConPower P20 / M17	ST- Serie	0,60	0,25	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS020	1607581	ConPower P20 / M17	ST- Serie	0,55	0,14	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS020	1607581	ConPower P20 / M17	ST- Serie	0,60	0,25	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS020	1607581	ConPower P20 / M17	ST- Serie	0,65	0,35	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS030	1607582	ConPower P20 / M17	ST- Serie	0,65	0,35	Stift 01
Phoenix Contact	97 59 63 PC1	ST-06KS030	1607582	ConPower P20 / M17	ST- Serie	0,73	0,50	Stift 01
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,46	0,06	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,50	0,08	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,53	0,14	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,65	0,25	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,69	0,34	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,80	0,50	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,85	0,75	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,90	1,00	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,84	AWG 18	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,57	AWG 22	1
Phoenix Contact	97 59 63 PC1	ST-10KP0,06-1,00	1243215	-	-	0,44	AWG 26	1
Phoenix Contact	97 59 63 PC1	ST-10KP010	1618255	-	-	0,48	0,06	1
Phoenix Contact	97 59 63 PC1	ST-10KP010	1618255	-	-	0,50	0,08	1
Phoenix Contact	97 59 63 PC1	ST-10KP010	1618255	-	-	0,55	0,14	1
Phoenix Contact	97 59 63 PC1	ST-10KP010	1618255	-	-	0,60	0,25	1
Phoenix Contact	97 59 63 PC1	ST-10KP035	1618458	-	-	0,65	0,25	1
Phoenix Contact	97 59 63 PC1	ST-10KP035	1618458	-	-	0,70	0,35	1
Phoenix Contact	97 59 63 PC1	ST-10KP035	1618458	-	-	0,78	0,50	1
Phoenix Contact	97 59 63 PC1	ST-10KP035	1618458	-	-	0,90	0,75	1
Phoenix Contact	97 59 63 PC1	ST-10KP035	1618458	-	-	1,00	1,00	1
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,40	0,06	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,45	0,08	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,53	0,14	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,62	0,25	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,69	0,34	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,74	0,50	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,78	0,75	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,85	1,00	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,86	AWG 18	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,57	AWG 22	3
Phoenix Contact	97 59 63 PC1	ST-10KS0,06-1,00	1243216	-	-	0,44	AWG 26	3
Phoenix Contact	97 59 63 PC1	ST-10KS010	1618239	-	-	0,48	0,06	3
Phoenix Contact	97 59 63 PC1	ST-10KS010	1618239	-	-	0,50	0,08	3
Phoenix Contact	97 59 63 PC1	ST-10KS010	1618239	-	-	0,55	0,14	3
Phoenix Contact	97 59 63 PC1	ST-10KS010	1618239	-	-	0,60	0,25	3
Phoenix Contact	97 59 63 PC1	ST-10KS035	1618464	-	-	0,65	0,25	3
Phoenix Contact	97 59 63 PC1	ST-10KS035	1618464	-	-	0,70	0,35	3
Phoenix Contact	97 59 63 PC1	ST-10KS035	1618464	-	-	0,78	0,50	3
Phoenix Contact	97 59 63 PC1	ST-10KS035	1618464	-	-	0,90	0,75	3
Phoenix Contact	97 59 63 PC1	ST-10KS035	1618464	-	-	1,00	1,00	3
Phoenix Contact	97 59 63 PC1	ST-20KP010	1607655	ConPower P20 / M17	ST- Serie	0,80	0,35	5
Phoenix Contact	97 59 63 PC1	ST-20KP010	1607655	ConPower P20 / M17	ST- Serie	0,88	0,50	5
Phoenix Contact	97 59 63 PC1	ST-20KP010	1607655	ConPower P20 / M17	ST- Serie	1,00	0,75	5
Phoenix Contact	97 59 63 PC1	ST-20KP010	1607655	ConPower P20 / M17	ST- Serie	1,10	1,00	5
Phoenix Contact	97 59 63 PC1	ST-20KS010	1607657	ConPower P20 / M17	ST- Serie	0,80	0,35	4
Phoenix Contact	97 59 63 PC1	ST-20KS010	1607657	ConPower P20 / M17	ST- Serie	0,88	0,50	4
Phoenix Contact	97 59 63 PC1	ST-20KS010	1607657	ConPower P20 / M17	ST- Serie	1,00	0,75	4
Phoenix Contact	97 59 63 PC1	ST-20KS010	1607657	ConPower P20 / M17	ST- Serie	1,10	1,00	4
Phoenix Contact	97 59 63 PC1	ST-20KS020	1607658	ConPower P20 / M17	ST- Serie	1,40	1,50	4
Phoenix Contact	97 59 63 PC1	ST-20KS020	1607658	ConPower P20 / M17	ST- Serie	1,65	2,50	4