Einstellwerte für gedrehte Kontakte
Settings for closed turned contacts

Werkzeuge / Tools
97 52 63 A / 97 52 63 DG A

Hinweis: Das Einstellmaß und die Locator-Position der Crimpzange sind entsprechend dem Leiterquerschnitt anzupassen.
Zur Ermittlung der hier aufgeführten Crimpeinstellungen wurde ein handelsübliches, feindrähtiges Litzenkabel verwendet. Die ermittelten Werte sind lediglich Richtgrößen und ohne Gewähr. Die Crimpeinstellungen sind vom Anwender mit der jeweils eingesetzten Litze konkret zu prüfen.

Note: The crimping depth and the locator position on the crimping tool must be adjusted to match the conductor cross-section.
A standard, fine-stranded cable was used to determine the crimping settings listed here. The values given are for guidance only and are provided without warranty.
The user must verify the crimping settings specifically for the stranded cable being used.

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator-position
Phoenix Contact	97 59 63 PC2	RC-10KP0,75-1,00	1241571	-	-	0,78	0,75	1
Phoenix Contact	97 59 63 PC2	RC-10KP0,75-1,00	1241571	-	-	0,79	1,00	1
Phoenix Contact	97 59 63 PC2	RC-10KS0,75-1,00	1241572	-	-	0,78	0,75	8
Phoenix Contact	97 59 63 PC2	RC-10KS0,75-1,00	1241572	-	-	0,79	1,00	8
Phoenix Contact	97 59 63 PC2	RC-11S2000	1596772	CA-Serie	RC - Serie	0,65	0,08	9
Phoenix Contact	97 59 63 PC2	RC-11S2000	1596772	CA-Serie	RC - Serie	0,67	0,14	9
Phoenix Contact	97 59 63 PC2	RC-11S2000	1596772	CA-Serie	RC - Serie	0,69	0,22	9
Phoenix Contact	97 59 63 PC2	RC-12S2000	1599600	CA-Serie	RC - Serie	0,63	0,14	9
Phoenix Contact	97 59 63 PC2	RC-12S2000	1599600	CA-Serie	RC - Serie	0,65	0,22	9
Phoenix Contact	97 59 63 PC2	RC-12S2000	1599600	CA-Serie	RC - Serie	0,67	0,38	9
Phoenix Contact	97 59 63 PC2	RC-12S2000	1599600	CA-Serie	RC - Serie	0,69	0,56	9
Phoenix Contact	97 59 63 PC2	RC-15KP0,08-0,56	1245475	-	-	0,44	0,08	7
Phoenix Contact	97 59 63 PC2	RC-15KP0,08-0,56	1245475	-	-	0,49	0,14	7
Phoenix Contact	97 59 63 PC2	RC-15KP0,08-0,56	1245475	-	-	0,59	0,25	7
Phoenix Contact	97 59 63 PC2	RC-15KP0,08-0,56	1245475	-	-	0,67	0,34	7
Phoenix Contact	97 59 63 PC2	RC-15KP0,08-0,56	1245475	-	-	0,72	0,50	7
Phoenix Contact	97 59 63 PC2	RC-15KP0,75-1,00	1244973	-	-	0,78	0,75	7
Phoenix Contact	97 59 63 PC2	RC-15KP0,75-1,00	1244973	-	-	0,79	1,00	7
Phoenix Contact	97 59 63 PC2	RC-15KS0,08-0,56	1245474	-	-	0,44	0,08	8
Phoenix Contact	97 59 63 PC2	RC-15KS0,08-0,56	1245474	-	-	0,49	0,14	8
Phoenix Contact	97 59 63 PC2	RC-15KS0,08-0,56	1245474	-	-	0,59	0,25	8
Phoenix Contact	97 59 63 PC2	RC-15KS0,08-0,56	1245474	-	-	0,67	0,34	8
Phoenix Contact	97 59 63 PC2	RC-15KS0,08-0,56	1245474	-	-	0,72	0,50	8
Phoenix Contact	97 59 63 PC2	RC-15P2000	1623779	CA-Serie	RC - Serie	0,80	0,50	6
Phoenix Contact	97 59 63 PC2	RC-15P2000	1623779	CA-Serie	RC - Serie	0,85	0,75	6
Phoenix Contact	97 59 63 PC2	RC-15P2000	1623779	CA-Serie	RC - Serie	0,95	1,00	6
Phoenix Contact	97 59 63 PC2	RC-15P2010	1623776	CA-Serie	RC - Serie	0,80	0,08	5
Phoenix Contact	97 59 63 PC2	RC-15P2010	1623776	CA-Serie	RC - Serie	0,85	0,14	5
Phoenix Contact	97 59 63 PC2	RC-15P2010	1623776	CA-Serie	RC - Serie	0,95	0,25	5
Phoenix Contact	97 59 63 PC2	RC-15P2020	1623777	CA-Serie	RC - Serie	0,65	0,14	3
Phoenix Contact	97 59 63 PC2	RC-15P2020	1623777	CA-Serie	RC - Serie	0,70	0,25	3
Phoenix Contact	97 59 63 PC2	RC-15P2020	1623777	CA-Serie	RC - Serie	0,75	0,35	3
Phoenix Contact	97 59 63 PC2	RC-15P2020	1623777	CA-Serie	RC - Serie	0,85	0,50	3
Phoenix Contact	97 59 63 PC2	RC-15P2030	1623778	CA-Serie	RC - Serie	0,75	0,50	4
Phoenix Contact	97 59 63 PC2	RC-15P2030	1623778	CA-Serie	RC - Serie	0,85	0,75	4
Phoenix Contact	97 59 63 PC2	RC-15P2030	1623778	CA-Serie	RC - Serie	0,95	1,00	4
Phoenix Contact	97 59 63 PC2	RC-15P2100	1623780	CA-Serie	RC - Serie	0,80	0,75	2
Phoenix Contact	97 59 63 PC2	RC-15P2100	1623780	CA-Serie	RC - Serie	0,85	0,75	2
Phoenix Contact	97 59 63 PC2	RC-15P2100	1623780	CA-Serie	RC - Serie	0,95	1,00	2
Phoenix Contact	97 59 63 PC2	RC-15P2200	1627292	CA-Serie	RC - Serie	0,70	0,08	7
Phoenix Contact	97 59 63 PC2	RC-15P2200	1627292	CA-Serie	RC - Serie	0,75	0,14	7
Phoenix Contact	97 59 63 PC2	RC-15P2200	1627292	CA-Serie	RC - Serie	0,80	0,25	7
Phoenix Contact	97 59 63 PC2	RC-15P2300	1627291	CA-Serie	RC - Serie	0,65	0,14	7
Phoenix Contact	97 59 63 PC2	RC-15P2300	1627291	CA-Serie	RC - Serie	0,70	0,25	7
Phoenix Contact	97 59 63 PC2	RC-15P2300	1627291	CA-Serie	RC - Serie	0,75	0,34	7
Phoenix Contact	97 59 63 PC2	RC-15P2300	1627291	CA-Serie	RC - Serie	0,80	0,50	7
Phoenix Contact	97 59 63 PC2	RC-15S2000	1623775	CA-Serie	RC - Serie	0,80	0,50	1
Phoenix Contact	97 59 63 PC2	RC-15S2000	1623775	CA-Serie	RC - Serie	0,85	0,75	1
Phoenix Contact	97 59 63 PC2	RC-15S2000	1623775	CA-Serie	RC - Serie	0,95	1,00	1
Phoenix Contact	97 59 63 PC2	RC-15S2200	1627290	CA-Serie	RC - Serie	0,70	0,08	8
Phoenix Contact	97 59 63 PC2	RC-15S2200	1627290	CA-Serie	RC - Serie	0,75	0,14	8
Phoenix Contact	97 59 63 PC2	RC-15S2200	1627290	CA-Serie	RC - Serie	0,80	0,25	8
Phoenix Contact	97 59 63 PC2	RC-1KS2000	1602998	CA-Serie	RC - Serie	0,75	0,50	9
Phoenix Contact	97 59 63 PC2	RC-1KS2000	1602998	CA-Serie	RC - Serie	0,80	0,75	9
Phoenix Contact	97 59 63 PC2	RC-1KS2000	1602998	CA-Serie	RC - Serie	1,00	1,00	9
Phoenix Contact	97 59 63 PC2	RC-1RKP0,08-0,56	1244971	-	-	0,44	0,08	5

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm²]	Locator- position
Phoenix Contact	97 59 63 PC2	RC-1RKP0,08-0,56	1244971	-	-	0,49	0,14	5
Phoenix Contact	97 59 63 PC2	RC-1RKP0,08-0,56	1244971	-	-	0,59	0,25	5
Phoenix Contact	97 59 63 PC2	RC-1RKP0,08-0,56	1244971	-	-	0,67	0,34	5
Phoenix Contact	97 59 63 PC2	RC-1RKP0,08-0,56	1244971	-	-	0,72	0,50	5
Phoenix Contact	97 59 63 PC2	RC-1RKP0,75-1,00	1244972	-	-	0,78	0,75	5
Phoenix Contact	97 59 63 PC2	RC-1RKP0,75-1,00	1244972	-	-	0,79	1,00	5
Phoenix Contact	97 59 63 PC2	RC-1RKP0,75-1,00/PE	1244974	-	-	0,80	0,75	4
Phoenix Contact	97 59 63 PC2	RC-1RKP0,75-1,00/PE	1244974	-	-	0,95	1,00	4
Phoenix Contact	97 59 63 PC2	RC-1RKS0,75-1,00	1244969	-	-	0,78	0,75	8
Phoenix Contact	97 59 63 PC2	RC-1RKS0,75-1,00	1244969	-	-	0,79	1,00	8